

RE-2AS MPE

Paging Microphone Expansion Unit

General

Expansion unit model RE-2AS MPE for the paging microphone RE-2AS MP8Z. It has 8 software programmable buttons for paging up to 8 public address zones. It has an iron chassis to provide stability and protection against damages. All buttons are designed for an intensive use.

Features

- 8 zones programmable buttons.
- Can connect up to 7 units to an RE-2AS MP8Z microphone.



Specification

Specification	
<i>Buttons</i>	8 x zone selection
<i>Operating Conditions</i>	-5°C to +45°C / 23°F to 113°F 5% to 95% relative humidity (no condensation)
<i>Material</i>	Fe 1,5 mm / 0,15"
<i>Color</i>	Grey RAL 7016 and Black RAL 9005
<i>Packaging dimensions (W x H x D)</i>	86 x 75 x 200 mm / 3.4" x 2.9" x 7.9"
<i>Dimensions (W x H x D)</i>	0,85 Kg / 1.9 lb
<i>Net weight</i>	380 x 100 x 320 mm / 15" x 3.9" x 12.6"
<i>Gross weight</i>	1,2 Kg / 2.6 lb
<i>Accessories</i>	Fixation elements, RE-2AS MP8Z connection and label for button identification

Ordering Information

Model	Description
RE-2AS MPE	Paging Microphone Expansion Unit

India

RAVEL ELECTRONICS PVT LTD.,
150A, Electronics Industrial Estate,
Perungudi, Chennai – 96, India.
E-mail: sales@ravelfire.com; Web: www.ravelfire.com

USA

RAVEL AMERICAS INC.,
2855 NW 112th Ave ST#2,
Doral, Florida 33172, USA.