RE-757M2

ADDRESSABLE DUAL MONITOR MODULE



General

The Dual Monitor Module facilitates third party devices to interface with Ravel addressable panels. DIP switches are provided for addressing of the module. This module is been supervised for the status (Alarm / Normal / Open). The dual monitor module shall use two successive addresses from the set address and this module shall use two electrically supervised inputs to monitor flow switches, sprinkler valves, fire dampers etc., The red blinking LED indicates normal operating condition and the steady state for activated condition.

Features

- UL listed 864 10th edition.
- 2 Supervised Conatct Monitoring Circuit.
- Status LED.
- Inbuilt isolator.
- SLC communication with the panel.
- DIP switches for addressing.
- Address between 1 249.
- Single gang box.







Specification

| Electrical Specification | | |
|--------------------------|--|--|
| Operating Voltage | 24 VDC Nominal | |
| Alarm Current | 2.3 mA (max) | |
| Standby Current | 1.1 mA | |
| End of Line Resistor | 47K ½ watt | |
| Wiring Resistance | 100 Ohms (max) | |
| Wiring Style | Class B | |
| Temperature Range | 0 – 49°C / 32 - 120°F | |
| Storage Temperature | 0 – 60°C / 32 - 140°F | |
| Humidity | 93 ± 2% RH (non-condensing) | |
| Mechanical Specification | | |
| IP rating | IP 40 | |
| Dimensions | (76.6L X 71.6W X 22D) mm (without gang holder) | |
| Dimensions | (125.5L X 85.5W X 22.2D) mm (with gang holder) | |
| Material | FRABS | |
| Weight | 70 g | |

Dimensions



Wiring Configuration



Compatible Panel

| Models | Description | |
|----------|---|--|
| Aaral X4 | Analogue Addressable Fire Alarm Control Panel expandable upto 4 loops | |
| Aaral X8 | Analogue Addressable Fire Alarm Control Panel expandable upto 8 loops | |

Compatible Device

| Models | Description |
|---------|--|
| RE-716P | Manual Pull station - single / dual action |
| RE-716M | Conventional Manual Call point |

Ordering Information

| Models | Description |
|----------|--|
| RE-757M2 | Analogue Addressable Dual Monitor Module |

(An ISO 9001 Company)

150A, Electronics Industrial Estate, Perungudi,

Chennai –600 096, India.

E-mail: marketing@ravelfire.com Web: www.ravelfire.com

*Ravel reserve the right to change the specification without prior notice.

USA

RAVEL AMERICAS INC., 2855 NW 112th Ave ST#2 Miami, Doral, Florida 33172, USA.